
























Device	Chip	RAM FLASH	Interface	Display	MEMS	Microphone	LED	IR	Button	Speaker	Li-Battery	Include
	ESP32-D0WDQ6-V3	520KB RAM 16MB Flash 8MB PSRAM	PortA(I2C)×1	2 inch, 320×240 Colorful TFT LCD, ILI9342C Touch Screen FT6336U	MPU6886	SPM1423	LED (green) x1	/	/	1W SPK@NS4168(I2S)	390mAh	CORE2 x 1 Type-C USB Cable x1 CORE2 EXT BOARD x1
	ESP32-D0WDQ6	520KB RAM 16MB Flash	PortA(I2C)×1 Extendable GPIO PINS	2 inch, 320×240 Colorful TFT LCD, ILI9342C	/	/	/	/	X3	1W-0928	110mAh	BASIC Core x 1 BASIC Bottom x 1 Type-C USB Cable x1 DuPont Cable x10 User Manual x1
	ESP32-D0WDQ6	520KB RAM 16MB Flash	PortA(I2C)×1 Extendable GPIO PINS	2 inch, 320×240 Colorful TFT LCD, ILI9342C	MPU6886 BMM150	/	/	/	X3	1W-0928	110mAh	GRAY Core x 1 GRAY Bottom x 1 Type-C USB Cable x1 DuPont Cable x10 User Manual x1
	ESP32-D0WDQ6	520KB RAM 16MB Flash 4MB PSRAM	PortA(I2C)×1 PortB(IO/ADC/ DAC)×1 PortC(UART)×1	2 inch, 320×240 Colorful TFT LCD, ILI9342C	MPU6886 BMM150	SPQ2410	SK6812 3535 RGB LED×10	/	X3	1W-0928	500mAh	FIRE Core x 1 M5GO Bottom x 1 M5GO Charge Basex1 Type-C USB Cable x1 LEGO Blocks x2 Allen Key x1 User Manual x1
	ESP32-D0WDQ6	520KB RAM 16MB Flash	PortA(I2C)×1 Extendable GPIO PINS	2 inch, 320×240 Colorful TFT LCD, ILI9342C	MPU6886 BMM150	/	/	/	X3	1W-0928	500mAh	GRAY Core x 1 Panels x 3(Keyboard、Gameboy、 Calculator) FACES Bottom x 1 FACES Charge Basex1 Type-C USB Cable x1 User Manual x1
	ESP32-D0WDQ6	520KB RAM 16MB Flash	PortA(I2C)×1 PortB(IO/ADC/ DAC)×1 PortC(UART)×1	2 inch, 320×240 Colorful TFT LCD, ILI9342C	MPU6886 BMM150	SPQ2410	SK6812 3535 RGB LED×10	/	X3	1W-0928	500mAh	M5GO Core x 1 M5GO Bottom x 1 Unit x6 (ENV, RGB, IR, ANGLE, HUB, PIR) CONNEXT Cable x4 LEGO Blocks x4 Type-C USB Cable x1 User Manual x1
	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) ×1 Extendable GPIO PINS	0.96" TFT LCD 80×160	MPU6886	SPM1423	RED LED×1	IR Transmitter x1	X2	/	95mAh	M5StickC x 1 Type-C USB Cable x1 Watch Belt x1(Optional) Wall/1515 x1(Optional) HAT(ENV,SPK) (Optional)
	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) ×1 Extendable GPIO PINS	1.14" TFT LCD 135×240	MPU6886	SPM1423	RED LED×1	IR Transmitter x1	X2	Buzzer	120mAh	M5StickC Plus x 1
	Kendryte K210	8Mbit RAM 16MB Flash	Port(I2C/UART/GPIO) ×1	1.14" TFT LCD 135×240	MPU6886	/	RGBW LED×1	/	X2	102828 Runway horn K60	200mAh	M5StickV x 1 Type-C USB Cable x1
	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) ×1 Extendable GPIO PINS	/	/	/	WS2812 RGB LED×1	IR Transmitter x1	X2	/	/	ATOM Lite x1
	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) ×1 Extendable GPIO PINS	/	MPU6886	/	WS2812 RGB LED 5×5	IR Transmitter x1	X2	/	/	ATOM Echo x1
	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) ×1 Extendable GPIO PINS	/	/	SPM1423	WS2812 RGB LED×1	IR Transmitter x1	X2	0.5W/NS4168 I2S	/	ATOM Echo x1

	ESP32-PICO-D4	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) x1 Extendable GPIO PINS MI-BUS	2.4 inch, 320x240 Colorful TFT LCD, ILI9342	/	/	LED (green) x1	/	PWR x1 RESET x1 EXT x1 Multi Function BTN x1	BUZZER	390mAh	COREINK x1 Type-C USB Cable x1
	ESP32-D0WDQ6-V3	520KB RAM 16MB Flash 8MB PSRAM	PortA(I2C)x1 PortB(IO/ADC/DAC)x1 PortC(UART)x1	4.7 inch, 960x540 16-level E- Ink CAP.TOUCH@GT911	/	/	/	/		/	1150mAh	M5PAPER x1

Device	Chip	RAM FLASH	Interface	ImageSensor	Lens Type	PM IC	RTC	Include
	ESP32-D0WDQ6-V3	520KB RAM 4MB Flash 8MB PSRAM	Port(I2C/UART/GPIO) x1	OV3660	Normal type Field of View:66.5 Degree	/	BM8563	TimerCAM-X x1 LEGO Accessories x 1 Type-C USB Cable x 1 Wall/1515 x1
	ESP32-D0WDQ6-V3	520KB RAM 4MB Flash 8MB PSRAM	Port(I2C/UART/GPIO) x1	OV3660	Normal type Field of View:66.5 Degree	/	BM8563	TimerCAM x1 LEGO Accessories x 1 Type-C USB Cable x 1 Wall/1515 x1
	ESP32-D0WD	520KB RAM 4MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Normal type Field of View:65 Degree	IP5306	/	ESP32 CAM x 1
	ESP32-D0WD	520KB RAM 4MB PSRAM 4MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Normal type Field of View:65 Degree	TP4057	/	M5Camera x 1 LEGO Accessories x 1 Type-C USB Cable x 1 User Manual Wall/1515 x1
	ESP32-D0WD	520KB RAM 4MB Flash 4MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Fish Eye Field of View:160 Degree	TP4057	/	M5CameraF x 1 LEGO Accessories x 1 Type-C USB Cable x 1 Wall/1515 x1
	ESP32-D0WD	520KB RAM 4MB PSRAM 4MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Normal type Field of View:65 Degree	TP4057	/	M5CameraX x 1 LEGO Accessories x 1 Type-C USB Cable x 1 Wall/1515 x1
	ESP32-D0WD	520KB RAM 4MB PSRAM 4MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Fish Eye Field of View:150 Degree	TP4057	/	M5CameraX x 1 LEGO Accessories x 1 Type-C USB Cable x 1 Wall/1515 x1
	Kendryte K210	8M RAM 16MB Flash	Port(I2C/UART/GPIO) x1	OV7740	Normal type Field of View:65 Degree	AXP192	/	M5StickV x 1 Type-C USB Cable x1
	Kendryte K210	8M RAM 16MB Flash	Port(I2C/UART/GPIO) x1	OV2640	Normal type Field of View:65 Degree	/	/	UnitV x 1 Type-C USB Cable x1 CONNEXT Cable x1